

# LOCTITE 362

March 2016

## PRODUCT DESCRIPTION

LOCTITE 362 provides the following product characteristics:

<b>Technology</b>	Solid flux
<b>Application</b>	Solder flux

## FEATURES AND BENEFITS

- Good wetting on most common surfaces
- Formulated for general work
- Non-corrosive
- Fast soldering
- Rosin based
- Halide activated

## TYPICAL PROPERTIES

### ALLOYS:

The alloys used in LOCTITE 362 cored solder wires conform to the purity requirements of the common national and international standards. A wide range of wire diameters is available manufactured to close dimensional tolerances.

### FLUX:

LOCTITE 362 solid flux leaves dry and non sticky residues. In use, its odor is typically that of rosin fluxes.

### FLUX PROPERTIES

Acid Value, mg KOH/g	170
Halide Content, %	<0.5
SIR Test (without cleaning), J-STD-004	PASS
J-STD-004 classification	ROL1
EN29451-1 classification	1.1.2

## DIRECTIONS FOR USE

### Soldering Iron:

Good results should be obtained using a range of tip temperatures. However, the optimum tip temperature and heat capacity required for a hand soldering process is a function of both soldering iron design and the nature of the task and care should be exercised to avoid unnecessarily high tip temperatures for excessive times. A high tip temperature will increase any tendency to flux spitting and it may produce some residue darkening.

The soldering iron tip should be properly tinned and this may be achieved using LOCTITE cored wire. Severely contaminated soldering iron tips should first be cleaned and pre-tinned using Multicore Tip Tinner/Cleaner, then wiped on a clean, damp sponge before re-tinning with LOCTITE cored wire.

### Soldering Process:

LOCTITE cored wires contain a careful balance of resins and activators to provide clear residues, maximum activity and high residue reliability, without cleaning in most situations. To achieve the best results from LOCTITE solder wires, recommended working practices for hand soldering should be observed as follows:

- Apply the soldering iron tip to the work surface, ensuring that it simultaneously contacts the base material and the component termination to heat both surfaces adequately. This process should only take a fraction of a second.
- Apply LOCTITE flux cored solder wire to a part of the joint surface away from the soldering iron and allow to flow sufficiently to form a sound joint fillet. This should be virtually instantaneous. Do not apply excessive solder or heat to the joint as this may result in dull, gritty fillets and excessive or darkened flux residues.
- Remove solder wire from the work piece and then remove the iron tip.

The total process will be very rapid, depending upon thermal mass, tip temperature and configuration and the solderability of the surfaces to be joined.

LOCTITE flux cored solder wires provide fast soldering on copper and brass surfaces as well as solder coated materials. Activity of the halide activated versions on nickel is also good depending on the state of oxidation of the nickel finish. The good thermal stability of Multicore fluxes means they are also well suited to soldering applications requiring high melting temperature alloys.

### Cleaning:

LOCTITE 362 cored solder wires have been formulated to leave pale flux residues and to resist spilling and fuming.

Cleaning will not be required in most situations but if necessary this is best achieved using LOCTITE MCF 800 Cleaner (see separate technical data sheet). Other proprietary solvent or semi-aqueous processes may be suitable. Saponification may be viable but customers must ensure that the desired level of cleanliness can be achieved by their chosen system.

### Surface Insulation Resistance

LOCTITE 362 flux pass the J-STD-004 SIR test and other elements of J-STD-004 test protocols associated with flux classification ROL1.

### Electromigration

LOCTITE 362 passes the Bellcore GR-78-CORE Electromigration test.

### DATA RANGES

The data contained herein may be reported as a typical value and/or a range. Values are based on actual test data and are verified on a periodic basis.

### GENERAL INFORMATION

**For safe handling information on this product, consult the Material Safety Data Sheet (MSDS).**

### Not for Product Specifications

The technical information contained herein is intended for reference only. Please contact Henkel Technologies Technical Service for assistance and recommendations on specifications for this product.

**Conversions** $(^{\circ}\text{C} \times 1.8) + 32 = ^{\circ}\text{F}$  $\text{kV/mm} \times 25.4 = \text{V/mil}$  $\text{mm} / 25.4 = \text{inches}$  $\mu\text{m} / 25.4 = \text{mil}$  $\text{N} \times 0.225 = \text{lb}$  $\text{N/mm} \times 5.71 = \text{lb/in}$  $\text{N/mm}^2 \times 145 = \text{psi}$  $\text{MPa} \times 145 = \text{psi}$  $\text{N}\cdot\text{m} \times 8.851 = \text{lb}\cdot\text{in}$  $\text{N}\cdot\text{m} \times 0.738 = \text{lb}\cdot\text{ft}$  $\text{N}\cdot\text{mm} \times 0.142 = \text{oz}\cdot\text{in}$  $\text{mPa}\cdot\text{s} = \text{cP}$ **Disclaimer****Note:**

The information provided in this Technical Data Sheet (TDS) including the recommendations for use and application of the product are based on our knowledge and experience of the product as at the date of this TDS. The product can have a variety of different applications as well as differing application and working conditions in your environment that are beyond our control. Henkel is, therefore, not liable for the suitability of our product for the production processes and conditions in respect of which you use them, as well as the intended applications and results. We strongly recommend that you carry out your own prior trials to confirm such suitability of our product.

Any liability in respect of the information in the Technical Data Sheet or any other written or oral recommendation(s) regarding the concerned product is excluded, except if otherwise explicitly agreed and except in relation to death or personal injury caused by our negligence and any liability under any applicable mandatory product liability law.

**In case products are delivered by Henkel Belgium NV, Henkel Electronic Materials NV, Henkel Nederland BV, Henkel Technologies France SAS and Henkel France SA please additionally note the following:**

In case Henkel would be nevertheless held liable, on whatever legal ground, Henkel's liability will in no event exceed the amount of the concerned delivery.

**In case products are delivered by Henkel Colombiana, S.A.S. the following disclaimer is applicable:**

The information provided in this Technical Data Sheet (TDS) including the recommendations for use and application of the product are based on our knowledge and experience of the product as at the date of this TDS. Henkel is, therefore, not liable for the suitability of our product for the production processes and conditions in respect of which you use them, as well as the intended applications and results. We strongly recommend that you carry out your own prior trials to confirm such suitability of our product.

Any liability in respect of the information in the Technical Data Sheet or any other written or oral recommendation(s) regarding the concerned product is excluded, except if otherwise explicitly agreed and except in relation to death or personal injury caused by our negligence and any liability under any applicable mandatory product liability law.

**In case products are delivered by Henkel Corporation, Resin Technology Group, Inc., or Henkel Canada, Inc. the following disclaimer is applicable:**

The data contained herein are furnished for information only and are believed to be reliable. We cannot assume responsibility for the results obtained by others over whose methods we have no control. It is the user's responsibility to determine suitability for the user's purpose of any production methods mentioned herein and to adopt such precautions as may be advisable for the protection of property and of persons against any hazards that may be involved in the handling and use thereof. In light of the foregoing, **Henkel Corporation specifically disclaims all warranties expressed or implied, including warranties of merchantability or fitness for a particular purpose, arising from sale or use of Henkel Corporation's products. Henkel Corporation specifically disclaims any liability for consequential or incidental damages of any kind, including lost profits.** The discussion herein of various processes or compositions is not to be

interpreted as representation that they are free from domination of patents owned by others or as a license under any Henkel Corporation patents that may cover such processes or compositions. We recommend that each prospective user test his proposed application before repetitive use, using this data as a guide. This product may be covered by one or more United States or foreign patents or patent applications.

**Trademark usage**

Except as otherwise noted, all trademarks in this document are trademarks of Henkel Corporation in the U.S. and elsewhere. ® denotes a trademark registered in the U.S. Patent and Trademark Office,

Reference 1

Americas

+1.888.943.6535

Europe

+32.1457.5611

Asia

+86.21.3898.4800

**For the most direct access to local sales and technical support visit: [www.henkel.com/electronics](http://www.henkel.com/electronics)**